



- The measurement of speaker systems actual impedance at 1 kHz.
- Three test ranges (20  $\Omega$  / 200  $\Omega$  / 2000  $\Omega$ ) allow testing of home theater and speaker system.
- LCD panoramic screen.
- It allows to estimate the necessary power in an installation for the suitable election of the amplifier.
- Data hold function.

## AUDIO IMPEDANCE TESTER

<b>Measurement range</b>	20 $\Omega$ / 200 $\Omega$ / 2000 $\Omega$
<b>Test frequency</b>	1 kHz
<b>Accuracy</b>	
<b>Range 20 <math>\Omega</math></b>	$\pm 2\%$ rdg $\pm 2$ dgt or $\pm 0.1$ W, which is greater.
<b>Range 200 W / 2000 <math>\Omega</math></b>	$\pm 2\%$ rdg $\pm 2$ dgt
<b>Presentation</b>	
<b>Display</b>	LCD 3 1/2 digit (2000 counts)
<b>Power supply</b>	
<b>Batterie</b>	9 V DC (6 batterie x 1.5V R6 type)
<b>Mechanical features</b>	
<b>Dimensions</b>	W. 90 x H. 205 x D. 55 (mm.)
<b>Weight</b>	Approx. 550 g (batteries included)
<b>Included accessories</b>	<b>PP010</b> Test leads set with safety clamps User's manual Transport suitcase